

# XLR CHASSIS CONNECTORS

#### 4 PIN JL SERIES

Locking 4 pin connectors with rugged metal shells perfect for use in DC power, aviation, communications, and other AV applications.



IO-XLR4-M-BK-JL

IO-XLR4-F-BK-JL

## **SPECIFICATIONS**

**PRODUCT** 

Gender: Male (IO-XLR4-M-BK-JL)

Female (IO-XLR4-F-BK-JL)

Contacts: 4

ELECTRICAL

Capacitance Between Contacts: ≤ 2 pF

Capacitance Between Contact and Ground: ≤ 2 pF

Contact Resistance:  $< 5 \text{ m}\Omega$ 

Insulation Resistance:  $\geq 5000M\Omega$ 

Dielectric Strength: 1500V @ 60s

Current Rating: 10A / 125V AC

Grounding: Separate ground terminal. Grounds to

mating connector shell

**ENVIRONMENTAL** 

Standard Compliance: IEC 61076-2-103

UL Flammability Rating: UL94 V-0

Temperature Range:  $-40^{\circ}$ C  $\sim +70^{\circ}$  C  $(-40^{\circ}$ F  $\sim +158^{\circ}$ F)

**MECHANICAL** 

Lifetime: > 1000 Mating Cycles

Wiring: Solder Contacts

Wiresize: 1.75mm Max O.D. (F)

1.20mm Max O.D. (M)

Locking Device: Latch Lock

Mounting Direction: Front

Solderability: Complies with IEC

60068-2-20

**MATERIAL** 

Pins: Brass (Male)

**Phosphor Bronze (Female)** 

Pin Plating: Silver

Grounding Terminal: Tin Plated Brass


Shell: Black Electrocoated Zinc Alloy

Push Button: Nickel Plated Brass

Latch: Nickel Plated Carbon Steel

# $I \cap$

#### **Panel Cutout**



#### **FEATURES & APPLICATIONS**

JL Series XLR chassis connectors offer a sleek and robust connection in a standard "J" Size shell. This series is perfect for high-noise environments like permanent installations or design-in applications where the termination method is solder cups. The connectors have nickel plated die cast zinc housing which allows for great RF protection. They have precision machined, one piece, silver plated contacts and a separate tin plated ground pin which grounds to the connector housing and panel. Available in either black or nickel housing and in 3, 4, or 5 pin variations. The JL Series XLR chassis connectors help prevent local RF interference from assisted listening, WiFi, and other radio transmitters close to the connectors. When coupled with quality shielded cables, a robust system for preventing the intrusion of unwanted noises is created.

#### PART NUMBER BREAKDOWN:

IO-XLR4-M-BK-JL
Series Identifier
IO-XLR4-M-BK-JL
Number of Pins
IO-XLR4-M-BK-JL
Gender
IO-XLR4-M-BK-JL
BK = Black Housing
(Blank) = Nickel Housing
IO-XLR4-M-BK-JL
Series Identifier

### **STANDARDS & CLASSIFICATIONS**

